



The **EB5000X** Industrial Generator From Honda

5000 watts of OSHA jobsite compliant, GFCI protected, industrial grade portable power. iAVR system allows for increased wattage above the maximum rating for up to 10 seconds to start high amp load applications. **New CO-MINDER™ advanced carbon monoxide detection system** continuously measures CO levels and automatically shuts down the generator before detected CO levels near the generator become dangerously high.*

FEATURES

- **5000 watts** (41.7/20.8A) 120/240V
- **Provides 7000 watts** (58.3/29.1A) 120/240V for 10 seconds to start larger equipment
- **GFCI/neutral bond protection**
- **Fuel efficient**, runs 10.5 hours at 1/2 load on 6.2 gallons of fuel
- **CO-MINDER™** automatically shuts down the generator if it detects carbon monoxide gas reaching unsafe levels
- **Standard wheel kit** with positive lock folding handles and hanger kit
- **120/240V selector switch**
- **Full frame protection** to prevent generator and fuel tank damage
- **Electronic ignition**
- **Circuit breakers**
- Protected by **Oil Alert®**
- **Honda 3-Year Residential Warranty/ Honda 3-Year Commercial Warranty†**



SPECIFICATIONS

EB5000X

Engine	Honda iGX390
Displacement	389cc
Max AC Output	5000w max. 120/240V (41.7/20.8A)
Rated AC Output	4500w rated (37.5/18.8A)
Receptacles	20A 125V GFCI Duplex (2) 30A 125V Locking Plug 30A 125/250V Locking Plug
Voltage Regulation	iAVR
Starting System	Recoil
Fuel Tank Capacity	6.2 gal
Run Time Per Tankful	7.1 hours at rated load 10.5 hours at 1/2 load
Noise Level**	65 dB(A) at rated load 63 dB(A) at 1/2 load
Dimensions (L x W x H)	41.1" x 27.8" x 30.4"††
Dry Weight	210.8 lbs.
USDA Spark Arrestor	Standard
CO-MINDER™	Standard



Find out more at gen.honda.com.

*This product complies with the ANSI/PGMA G300-2018 standard. †Warranty applies to all Honda GX Series Engines and GX Series-powered Honda Power Equipment, 100cc or larger, purchased or put into rental service since January 1, 2010. Exceptions apply. See full warranty details at honda.com. Does not apply to EU1000 models. **Tested in accordance with ISO 9614-2, sound pressure level calculated at 23 Feet (7 meters) using the front plane of the generator (control panel side) per ASHRAE Handbook 2017. ††Including hanging hook and with handles folded. Please read the owner's manual before operating your Honda Power Equipment and never use in a closed or partly enclosed area where you could be exposed to odorless, poisonous carbon monoxide. Connection of a generator to house power requires a transfer device to avoid possible injury to power company personnel. Consult a qualified electrician. © 2020 American Honda Motor Co., Inc. C1032